

Requires 0U vertical outlet strip accessory (sold separately).

- PDU3V602D354 (54 C13 outlets)
- PDU3V602D354A (42 C13 and 12 C19 outlets)
- PDU3V602D354B (48 C13 and 6 C19 outlets)

#### PowerAlert Console Launcher

To address Java Runtime Environment (JRE) issues with respect to the [SNMPWEBCARD](#) web interface, Tripp Lite recommends using the [PowerAlert Console Launcher](#). This application enables local access of the [SNMPWEBCARD](#) using a self-contained, compatible JRE version. The Console Launcher can be downloaded for free from the link above, the [SNMPWEBCARD Support](#) page, or from the Management Solutions / Utilities page.

## 17.3kW 3-Phase 208V ATS/Monitored PDU, 2 IEC 309 60A Inputs, 1U Rack-Mount (0U Outlet Accessory Sold Separately), TAA

MODEL NUMBER: PDU360AT6G60



High-capacity 17.3kW PDU with patented ATS provides remote power monitoring and enables redundant power for network devices. LED display and Ethernet interface help you monitor load levels to prevent overloads that cause downtime.

#### Description

Tripp Lite's patented PDU360AT6G60 17.3kW 3-Phase 208V ATS/Monitored PDU (U.S. Patent 9,467,006) provides rapid coordination of unsynchronized phases without dropping loads. It operates with the high efficiency and reliability required for data center applications.

Working in tandem with a required 0U vertical outlet accessory (sold separately; choose from PDU3V602D354, PDU3V602D354A or PDU3V602D354B), the 1U PDU360AT6G60 provides remote power monitoring and enables redundant power for network devices with non-redundant power supply configurations.

Dual 6.5-foot input cords with IEC 309 60A Blue (3P+E) plugs connect to separate primary and secondary 3-phase power sources. The PDU constantly evaluates the power quality of both input sources. Dynamic

#### Highlights

- Requires Tripp Lite 0U outlet accessory (sold separately)
- 3-phase IEC 309 60A Blue (3P+E) input and single-phase 208V output
- Automatic transfer switching within 1–5 ms
- Ethernet network interface for remote access
- Patented ATS technology

#### Package Includes

- PDU360AT6G60 17.3kW 3-Phase 208V ATS/Monitored PDU
- Rack-mounting hardware
- Configuration cable
- Owner's manual

solid-state (TRIAC) automatic transfer switching allows the PDU to switch to the secondary source within 1–5 milliseconds should the primary source fail or become unstable to ensure your connected equipment operates without interruption.

Built-in Ethernet network interface allows remote access to the PDU for power monitoring, configuration, control and notifications via web browser, SSH, telnet or SNMP. Provides real-time load/current data with billing-grade accuracy (+/- 1 percent). Digital LED display indicates power availability, voltage, source A/B input status, output load and power factor.

## Features

### Primary and Secondary Inputs for Power Redundancy

- Provides remote power monitoring and enables redundant power for network devices with non-redundant power supply configurations
- Dual 6.5 ft. input cords with IEC 309 60A Blue (3P+E) plugs connect to separate primary and secondary 3-phase power sources

### Automatic Transfer Switching

- Dynamic solid-state (TRIAC) automatic transfer switching
- Patented ATS technology provides rapid coordination of unsynchronized phases without dropping loads
- Switches to secondary power source if primary source fails or becomes unstable
- 1–5 ms transfer time ensures uninterrupted operation of connected equipment

### Multifunction Digital LED Display

- Reports source A and source B input power status and other information, including power availability, line voltage, frequency, amps, kilowatts and power factor

### Advanced Network Monitoring

- Built-in Ethernet network interface allows full remote access for power monitoring, configuration, control and notifications via web browser, SSH, telnet or SNMP
- Real-time load/current data with billing-grade accuracy (+/- 1 percent)
- Tiered access privileges allow both an administrator and a guest to log in
- Automated alerts help prevent accidental overloads, power loss and downtime
- Supports centralized management through NMS or DCIM platform
- Optional ENVIROSENSE module (sold separately) monitors temperature and humidity

### Broad Communications Compatibility

- Supports HTTP, HTTPS, PowerAlert®, SMTP, SNMPv1, SNMPv2, SNMPv3, Telnet, SSH, FTP, DHCP, BOOTP and NTP

### 0U Vertical Outlet Accessory Required

- Requires separate installation of Tripp Lite PDU3V602D354, PDU3V602D354A or PDU3V602D354B power strip (sold separately)



- 20A circuit breakers protect each single-phase load bank
- Supports 0U toolless button-mount rack mounting

#### Mounts Horizontally in 1U of Rack Space

- Compatible with EIA-standard 19 in. 4-post racks and rack enclosures

#### TAA-Compliant

- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases

## Specifications

OVERVIEW	
UPC Code	037332192905
PDU Type	Monitored; Auto-Transfer Switch
OUTPUT	
Frequency Compatibility	60 Hz
Output Receptacle Details	Vertical output power distribution component is a REQUIRED separate-purchase accessory; Order from these options: PDU3V602D354 (54 C13 outlets), PDU3V602D354A (42 C13 and 12 C19 outlets) or PDU3V602D354B (48 C13 and 6 C19 outlets)
Output Capacity Details	17.3kW (208V) total capacity; 27.8A max per output phase (L1-L2, L2-L3, L3-L1), 13.9A max per breakered load bank (C1-C6)
Output Receptacles	C13; C19
Output Nominal Voltage	208
Overload Protection	Required vertical power distribution component contains six 20A double-pole breakers, one per breakered output load bank (C1-C6)
INPUT	
PDU Input Voltage	208
Maximum Input Amps	48
PDU Plug Type	(2) IEC-309 60A BLUE (3P+E)
Input Phase	3-Phase
Input Cord Details	Set of 2 inputs enable connection to separate PRIMARY and SECONDARY power sources
Input Cord Length (ft.)	6.5
Input Cord Length (m)	1.98
USER INTERFACE, ALERTS & CONTROLS	
Reported Load Segments	Supports local display of A & B line INPUT CURRENT, INPUT VOLTAGE & FREQUENCY per phase, OUTPUT CURRENT, KW, VOLTAGE & POWER FACTOR per output phase combination (L1-L2, L2-L3, L3-L1), TOTAL OUTPUT POWER (kW), PHASE IMBALANCE (%), TEMPERATURE (C/F), FAULT CODE and SCROLL IP



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

Front Panel LCD Display	Large 3-character display reports data for reported values; Additional 2 character digital display identifies the measurement value or specific location the displayed measurement applies
Front Panel LEDs	Set of 6 LEDs indicate A/B input PREFERRED, AVAILABLE & IN USE status; Set of 5 LEDs label the measurement value displayed (AMPS, KW, VOLTS, HZ & POWER-FACTOR); One additional red LED reports BREAKER TRIP status
Switches	MODE and ENTER buttons enable navigation and viewing of all reported information
Current Measurement Accuracy (Amps)	+/-1%
Voltage Measurement Accuracy (Volts)	+/-1%
Power Measurement Accuracy (Watts)	+/-1%
<b>PHYSICAL</b>	
Shipping Dimensions (hwd / in.)	7.90 x 27.90 x 38.50
Shipping Dimensions (hwd / cm)	20.07 x 70.87 x 97.79
Shipping Weight (lbs.)	53.00
Shipping Weight (kg)	24.04
Unit Dimensions (hwd / in.)	1.72 x 16.9 x 26
Unit Dimensions (hwd / cm)	4.4 (1U) x 43 x 66
Unit Weight (lbs.)	26.8
Unit Weight (kg)	12.16
Material of Construction	Steel
Form Factors Supported	1U rackmount ATS module; Separate purchase 0u vertical mount PDU outlet distribution bar sold separate (3 options available)
PDU Form Factor	Horizontal (1U)
<b>ENVIRONMENTAL</b>	
Storage Temperature Range	5 to 122F (-15 to 50C)
Relative Humidity	Up to 95% (non-condensing)
Operating Elevation (ft.)	0-10,000
Operating Elevation (m)	0-3000
<b>SPECIAL FEATURES</b>	
Grounding Lug	Included
<b>CERTIFICATIONS</b>	
Certifications	Tested to UL/CSA 60950-1 (USA, Canada), NOM (Mexico), FCC Class A (Emissions), RoHS Complaint, TAA Compliant
<b>WARRANTY</b>	



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

Product Warranty Period (Worldwide)	2-year limited warranty
--	-------------------------

© 2019 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies:  
<https://www.tripplite.com/products/product-certification-agencies>