

# Datamate L-Tek Connectors

## Spare Male Crimp Contacts

- Barrel Crimp Contacts are supplied with the connectors - see previous page. Use the order code for extra Spare crimps.



CRIMP CONTACTS	WIRE STRIPPING DETAILS										
<p><b>Large Bore (22 AWG)</b></p>											
<p><b>Small Bore (24 to 28 AWG)</b></p>	<p style="background-color: #f4a460; padding: 2px;"><b>TOOLS</b></p> <p><b>Recommended Crimp Tool</b> - M22520/2-01  <b>Positioner</b> - T5747  <b>Contact Insertion/Removal Tool</b> - Z80-280</p> <p>❖ Instruction sheets available at <a href="http://www.harwin.com/instructions">www.harwin.com/instructions</a>.</p>										
HOW TO ORDER											
<p><b>M80 - 04X 00 05</b></p>											
<p style="background-color: #f4a460; padding: 2px;">SERIES CODE</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr style="background-color: #f4a460;"> <th colspan="2">TYPE</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;"><b>040</b></td> <td>Large Bore (22 AWG)</td> </tr> <tr> <td style="text-align: center;"><b>041</b></td> <td>Small Bore (24-28 AWG)</td> </tr> </tbody> </table>	TYPE		<b>040</b>	Large Bore (22 AWG)	<b>041</b>	Small Bore (24-28 AWG)	<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr style="background-color: #f4a460;"> <th colspan="2">FINISH</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;"><b>05</b></td> <td>Gold</td> </tr> </tbody> </table>	FINISH		<b>05</b>	Gold
TYPE											
<b>040</b>	Large Bore (22 AWG)										
<b>041</b>	Small Bore (24-28 AWG)										
FINISH											
<b>05</b>	Gold										

All dimensions in mm.