

Main

Mani	
Range of Product	Lexium Altivar
Product or Component Type	EMC input filter
Range Compatibility	Altivar 32 Altivar Machine ATV320 Lexium 28
Product compatibility	LXM28A ATV32, 200240 V, 2.2 kW Variable speed drive ATV320B 2.2 kW, 200240 V, single phase
Product Specific Application	Radio interference input filter
Mounting Location	At variable speed drive side
Phase	Single phase

Complementary

Maximum cable distance between devices	65.62 Ft (20 m) IEC 61800-3 category C1 164.04 ft (50 m) IEC 61800-3 category C2	
Line Rated Current	23.9 A	
Thermal losses	7.5 W	
Network rated voltage	200240 V	
Tolerance	- 1510 %	
Net Weight	2.49 lb(US) (1.13 kg)	
Emc filter compatibility	Type 026	

Ordering and shipping details

22452 ATV220/ATV242/ATV22 / 25 THRILT SHRV		
22152 - ATV320/ATV312/ATV32 (.25 THRU 7.5HP)		
CP4B		
3606480320897		
1		
31.04 oz (880 g)		
No		
TH		

Packing Units

Unit Type of Package 1	PCE	
Package 1 Height	2.24 in (5.7 cm)	
Package 1 width	8.94 in (22.7 cm)	
Package 1 Length	10.83 in (27.5 cm)	
Unit Type of Package 2	S04	
Number of Units in Package 2	11	
Package 2 Weight	23.54 lb(US) (10.678 kg)	
Package 2 Height	11.81 in (30 cm)	
Package 2 width	15.75 in (40 cm)	
Package 2 Length	23.62 in (60 cm)	

Offer Sustainability


California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov		
REACh Regulation	☐ REACh Declaration		
REACh free of SVHC	Yes		
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)		
Toxic heavy metal free	Yes		
Mercury free	Yes		
RoHS exemption information	₫Yes		
China RoHS Regulation	☑ China RoHS Declaration		

Contractual warranty

\	40	
Warranty	18 months	

VW3A4426

Additional EMC Input Filters



Dimensions in mm


а	b	С	G	Н	Ø
140	235	35	120	215	4.5

Dimensions in in.


а	b	С	G	Н	Ø
5.51	9.25	1.38	4.72	8.46	0.18

Mounting Recommendations

Mounting the Filter on the Side of the Drive



Recommended Schema



- (1) Filter (2) Drive